

## **High Voltage MOSFET**

N-Channel, Enhancement Mode


IXTU 01N80 IXTY 01N80


 $V_{DSS}$  = 800 V  $I_{D25}$  = 100mA  $R_{DS(on)}$  = 50  $\Omega$ 

Preliminary data sheet



$V_{\text{DSS}}$ $T_{\text{J}} = 25^{\circ}\text{C to } 150^{\circ}\text{C}$ 800	V
$V_{DGR}$ $T_{J} = 25^{\circ}\text{C to } 150^{\circ}\text{C}; R_{GS} = 1 \text{ M}\Omega$ 800	V
V <sub>cs</sub> Continuous ±20	V
V <sub>GSM</sub> Transient ±30	V
$I_{D25}$ $T_{C} = 25^{\circ}C; T_{J} = 25^{\circ}C \text{ to } 150^{\circ}C$ 100	mA
$I_{DM}$ $T_{C} = 25^{\circ}C$ , pulse width limited by max. $T_{J}$ 400	mA
$\overline{P_{D}}$ $T_{C} = 25^{\circ}C$ 25	W
T <sub>J</sub> -55 +150	°C
$T_{JM}$ 150	°C
<b>T</b> <sub>stg</sub> -55 +150	°C
T <sub>L</sub> 1.6 mm (0.063 in) from case for 5 s 300	°C
Weight 0.8	g





G = Gate, D = Drain, S = Source, TAB = Drain

Symbol	<b>Test Conditions</b>	$(T_J = 25^{\circ}C, \text{ unless of } $	istic Va se speci max.	
V <sub>DSS</sub>	$V_{_{\mathrm{GS}}}$ = 0 V, $I_{_{D}}$ = 25 $\mu A$	800		V
V <sub>GS(th)</sub>	$V_{_{DS}} = V_{_{GS}}$ , $I_{_{D}} = 25 \mu A$	2	4.5	V
I <sub>GSS</sub>	$V_{GS} = \pm 20 V_{DC}, V_{DS} = 0$		±50	nA
I <sub>DSS</sub>	$V_{DS} = 0.8 V_{DSS}$ $V_{GS} = 0 V$	T <sub>J</sub> = 25°C T <sub>J</sub> = 125°C	10 200	μ <b>Α</b> μ <b>Α</b>
R <sub>DS(on)</sub>	$V_{GS} = 10 \text{ V}, I_{D} = I_{D25}$ Pulse test, $t \le 300 \text{ ms}$ , duty	/ cycle d ≤ 2 %	50	Ω

## **Features**

- International standard packages
  JEDEC TO-251 AA, TO-252 AA
- $^{ullet}$  Low R<sub>DS (on)</sub> HDMOS<sup>TM</sup> process
- Rugged polysilicon gate cell structure
- Fast switching times

## **Applications**

- Level shifting
- Triggers
- Solid state relays
- Current regulators



Symbol		Characteristic Values unless otherwise specified)		
	min.		max.	
$g_{fs}$	$V_{DS} = 10 \text{ V}; I_{D} = 0.5 I_{D25}, \text{ pulse test}$	140		mS
C <sub>iss</sub>		60		pF
C <sub>oss</sub>	$V_{GS} = 0 \text{ V}, V_{DS} = 25 \text{ V}, f = 1 \text{ MHz}$	8.0		pF
$\mathbf{C}_{rss}$	J	2.0		pF
t <sub>d(on)</sub>	)	12		ns
t <sub>r</sub>	$V_{GS} = 10 \text{ V}, V_{DS} = 500 \text{ V}, I_{D} = I_{D25}$	12		ns
$\mathbf{t}_{d(off)}$	$R_{\rm G} = 50 \Omega $ (External)	28		ns
t,	)	28		ns
Q <sub>g(on)</sub>	)	8		nC
$Q_{gs}$	$V_{GS} = 10 \text{ V}, V_{DS} = 0.5 V_{DSS}, I_{D} = 0.5 I_{D25}$	1.8		nC
$\mathbf{Q}_{gd}$	J	3		nC
R <sub>thJC</sub>			3	K/W

TO-251 AA Outline						
b b c b c b c b c b c b c b c b c b c b						
Dim.	Milli Min.	imeter Max.	Inch Min.	nes Max.		
l .						
A A1	2.19 0.89	2.38 1.14	.086 0.35	.094 .045		
b	0.64	0.89	.025	.035		
b1	0.76	1.14	.030	.045		
b2	5.21	5.46	.205	.215		
С	0.46	0.58	.018	.023		
اسا						
c1	0.46	0.58	.018	.023		
D	0.46 5.97	0.58 6.22	.018	.023		
l —						
D	5.97 6.35 2.28	6.22 6.73 BSC	.235 .250 .090	.245 .265 BSC		
D E	5.97 6.35	6.22 6.73	.235	.245		
D E e	5.97 6.35 2.28	6.22 6.73 BSC	.235 .250 .090	.245 .265 BSC		
D E e e1 H	5.97 6.35 2.28 4.57 17.02 8.89	6.22 6.73 BSC BSC 17.78 9.65	.235 .250 .090 .180 .670	.245 .265 BSC BSC .700		
D E e e1 H L	5.97 6.35 2.28 4.57 17.02 8.89 1.91	6.22 6.73 BSC BSC 17.78 9.65 2.28	.235 .250 .090 .180 .670 .350 .075	.245 .265 BSC BSC .700 .380		
D E e e1 H L L1 L2	5.97 6.35 2.28 4.57 17.02 8.89 1.91 0.89	6.22 6.73 BSC BSC 17.78 9.65 2.28 1.27	.235 .250 .090 .180 .670 .350 .075 .035	.245 .265 BSC BSC .700 .380 .090		
D E e e1 H L	5.97 6.35 2.28 4.57 17.02 8.89 1.91	6.22 6.73 BSC BSC 17.78 9.65 2.28	.235 .250 .090 .180 .670 .350 .075	.245 .265 BSC BSC .700 .380		

## Source-Drain Diode **Characteristic Values** $(T_{\perp} = 25^{\circ}C, \text{ unless otherwise specified})$ **Symbol Test Conditions** min. typ. | max. $I_{_F}$ = 100 mA, $V_{_{\rm GS}}$ = 0 V, Pulse test, $t \leq 300~\mu s,$ duty cycle d $\leq$ 2 % $\mathbf{V}_{\mathrm{SD}}$ 1.5 ٧ $$\begin{split} I_{_F} &= 0.75 \text{ A, -di/dt} = 10 \text{ A/}\mu\text{s,} \\ V_{_{DS}} &= 25 \text{ V} \end{split}$$ 1.5 $\mu$ s t<sub>rr</sub>

